

## Microwave programmable 1800W

281369

Housing and interior of the chamber made of stainless steel. Chamber fitted with a ceramic floor. Lower and upper rotating microwave antennas for uniform energy distribution, no rotating parts in the chamber. Built-in air filter protects against dust and dirt. Easy to read control panel, select the desired program on the touch panel. Door with large window for observing processes in the illuminated microwave chamber. Tight latch closure; easy opening – no locking mechanism. Chamber interior: – dimensions 360x409x(H)225 mm, capacity 34 L. – easy to clean. – no breaking of plates thanks to appropriately rounded edges. – ceramic bottom. Multifunctional use: – defrosting. – 10 default programs. – possibility to save up to 100 programs (up to 3 stages per program). – automatic time conversion for double portions. – the end of the cooking cycle is signalled by an acoustic alarm. Microwave power: 1800 W. Suitable for round (up to ø355 mm) and rectangular plates. Maximum single operating time: 60 minutes. Fitted with a grounded plug. Weight: 32.3 kg.



### Specifications

Voltage	: 230
Electrician needed	: No
Materials	: Stainless steel
Packed per	: 1
Length (mm)	: 572
Width (mm)	: 520
Height (mm)	: 363
Internal length (mm)	: 409
Internal width (mm)	: 360
Internal height (mm)	: 225
Usable volume (L)	: 34
Power (input) (W)	: 3000
Power (output) (W)	: 1800
Control panel	: Digital
Programmable	: Yes
Measurements	: 572x520x(H)363

### Transport specifications

EAN	: 8711369281369
Intrastat code	: 85165000
Gross weight (kg)	: 35.59
Net weight (kg)	: 33.19
Sales units per pallet	: 6
Plastic packaging (gram)	: 459

#### HENDI B.V.

Innovatielaan 6  
6745 XW De Klomp, The Netherlands  
T: +31 (0)317 681 040  
E: info@hendi.eu

#### HENDI Polska Sp. z o.o.

ul. Firmowa 12  
62-023 Robakowo, Poland  
T: +48 61 6587000  
E: info@hendi.pl

#### HENDI GmbH

Ehring 15  
5112 Lamprechtshausen, Austria  
T: +43 (0) 6274 200 10 0  
E: office.austria@hendi.eu

#### HENDI S.R.L.

Str. 13 decembrie 94A, Hala 14  
Braşov, 500164, Romania  
T: +40 268 320330  
E: office@hendi.ro

#### PKS HENDI South East Europe SA

5 Metsovou Str.  
18346 Moschato, Athens, Greece  
T: +30 210 4839700  
E: info@pks-hendi.com

#### HENDI Italia S.R.L.

Via Leonardo da Vinci 4  
39100 Bolzano (BZ), Italy  
T: 800 727 438  
E: office.italy@hendi.eu